

WMS GAMES

PARTS AND SERVICE INC.


3401 N. CALIFORNIA AVE. CHICAGO, IL 60618 (312)509-6544

SERVICE TIP

SUBJECT: JOKERZ AUDIO HUM

THE FOLLOWING MODIFICATIONS SHOULD BE MADE TO THE SYSTEM 11B BOARD (CPU) IN THE SOUND SECTION TO REDUCE NOISE IN THE JOKERZ PINBALL GAME.

1. PIN 1 OF U3 MUST BE ISOLATED FROM THE +5VDC SUPPLY.



2. BOTH CUTS MUST BE MADE.
3. THEN ADD A 10 μ F CAPACITOR FROM PIN 1 TO PIN 2 ON I.C. U3, WITH THE POSITIVE SIDE SOLDERED TO PIN 1.
4. ADD A 1 K OHM RESISTOR FROM U3 PIN 1 TO U9 PIN 20.
5. MAKE SURE YOU HAVE NO LESS THAN CPU EPROM REV. 6 AND SOUND EPROM REV. 2

THESE MODIFICATIONS WILL GREATLY REDUCE NOISE IN THE AUDIO SYSTEM.